

Klein RESCUE Remote Speaker Microphone

The RESCUE Remote Speaker Microphone (RSM) has a built-in amplifier for ultra-loud and clear audio, tested to deliver 104dB output.

Klein custom designed the RESCUE RSM to reliably connect to Sonim's SecureAudio Connector on the XP5s and XP8 handsets. This allows the RESCUE RSM connector to screw into the handsets and draw power. The RESCUE RSM contains a directional microphone for noise cancellation, large PTT button and orange programmable button.

Did You Know?

The RESCUE RSM features a headset port to connect a listen-only headset. A listen-only headset redirects the receive audio through the headset, while still transmitting audio through the RSM. This is necessary when in a situation where you don't want audio broadcasted from the RSM.

Features

- Push-to-Talk simplex and full-duplex Remote Speaker Microphone
- Built-in amplifier for loud and clear audio
- Large and tactile PTT and emergency buttons
- Ergonomic slim profile is comfortable to use and wear
- Audio port for listen-only headset
- Optional listen-only headsets, eartips and in-vehicle holder available
- Omni-Directional Back Electret Condenser Microphone
- Microphone Sensitivity at 1kHz -39 to -33dB
- Microphone Output Impedance at 1kHz 300 Max Ω
- Microphone Signal / Noise Ratio at 1kHz 65+dB
- Speaker Input Power 1W (Max 1.5W)
- Speaker Output Level (SPL) 104 +/- 3dB
- Speaker Resonant Frequency 650 +/-20% HZ @ 1V
- Speaker Impedance 8 Ω
- Speaker Sensitivity 95 +/- 3dB
- Speaker Distortion Factor 5% Max
- Compatible with Sonim XP5s and XP8 handsets
- Designed and Assembled in the USA
- Third party lab tested to meet IP-67 rating standard
- 3 Year Comprehensive Warranty
- Operating Temperature -25C to +50C
- Klein RESCUE Length 100 inches, Weight 181g
- Packaged Product Dimensions 6 x 4 x 2.5 inches, Weight 233g

